

	HT1106XS	HT1106XL	HT1110XS	HT1110XL
<b>INPUT</b>				
Cold Start	YES Default output frequency will be 50Hz or settable			
Acceptable Input Voltage	110VAC~288VAC			
	100% load@>176VAC			
	90% load@>154VAC			
	75% load@>132VAC			
	50% load@>110VAC			
Phase	Single phase in, single phase out			
Transfer Voltage Range	200VAC/208VAC(0.9), 220VAC/230VAC/240VAC(1)			
-Line low transfer	110VAC			
-Line low recovery	121VAC			
-Line high transfer	288VAC			
-Line high recovery	281VAC			
<b>Input Current</b>				
-Rated nominal input current	30A/220V	34A/220V	49A/220V	53A/220V
Input Power Factor	≥0.99			
Input current distortion	<4%			
Input Frequency Range	40~70Hz			
<b>OUTPUT</b>				
Frequency adaptable	Settable			
Power				
-Power	6KVA		10KVA	
-Power(kW)	6KW		10KW	
Output Voltage				
-Waveform(Bat. Mode)	Pure Sine Wave			
-Nominal voltage	220VAC/230VAC/240VAC, 200VAC/208VAC(PF=0.9)			
-Voltage regulation	± 1 %			
-Voltage distortion	≤ 1% THD, linear load ≤ 5% THD, non linear load			
Output Frequency				
-Synchronization range	±5Hz default, settable			
-Battery mode	(50±0.1) Hz default			
<b>Transfer Time</b>				
-Line mode to battery mode	0ms			
-Inverter to bypass	0ms			
<b>Efficiency</b>				
-Line mode with battery full charged	94.6% @ 100% load, 95% @ 60% load			
-ECO mode	98.0%			
Noise(1m away)	<58dB			
<b>Overload Capability(Inverter)</b>				
	105% to 110% : Transfer to bypass after 10 mins.			
	111% to 125% : Transfer to bypass after 1 mins.			
	126% to 150%: Transfer to bypass after 30s			
<b>Overload Capability (Bypass Mode)</b>				
	less than 125%: long time running			
	126% to 130% :Shutdown in 5 mins			
	131% to 150% :Shutdown in 1 mins			
	> 150% :Shutdown in 200 ms			
Crest Ratio	3:1			
<b>BATTERY</b>				
Rating/Type	12VDC/7Ah	Depend on the capacity of external batteries	12VDC/9Ah	Depend on the capacity of external batteries
Quantity	16PCS default, 20PCS settable	16-20PCS settable	16PCS default, 20PCS settable	16-20PCS settable
DC Voltage	192VDC default, settable			
Back-up Time	3mins @ 5kW	Depend on the capacity of external batteries	2mins @ 8kW	Depend on the capacity of external batteries
<b>Charger</b>				
-Charging current (max)	1A, settable	5A max, settable	1A, settable	5A max, settable
-Float Charging Voltage	2.25V/cell default, settable via software			
-Boost Charging Voltage	2.25V/cell default, settable via software			
-Charging time	8h recharge to 90%	Depend on the capacity of external batteries	8h recharge to 90%	Depend on the capacity of external batteries
Leakage current	<3mA			
<b>Indicator &amp; Alarm</b>				
-Display	LED+LCD			
<b>Interface</b>				
-Smart RS232	Standard Cable support Power Monitor Software			
-EPO	NC			
-RS485(option)	Installed in the intelligent slot			
-SNMP(option)	Power Management from SNMP Manager and Web Browser			
<b>Option</b>				
-Intelligent Kits	DB9 port, dry contact			
-parallel	4 units paralleled			
-Super charger (12A)	digitally controlled, 4-steps charge, settable, @PF0.9			
-USB	B-type USB port			
-SNMP Kits	Pluggable type			
Working Environment				
<b>Mechanical</b>				
-W×D×H (mm)	190*426*705	190*426*336	190*485*705	190*485*336
-Net Weight (KG)	56	14	66	16
-Package Weight (KG)	61	15	73	17
-Rack / Tower	Tower			
Color	Black default			

<b>FUNCTION</b>	Compatible with half wave load
	Main input breaker
	Bypass input breaker
	ECO mode
	Battery cabinet
	Self aging
	Digital Charger
	Remained Battery Capacity
	12A charger (PF will be de rated to 0.9)